JLH-213 WIRELESS TRANSMITTER & RECEIVER KIT

Experience the Difference,
Simplicity and Creativity.

Back

Front

JLH-213

Specifications

Ideal Applications

- Art Gallery
- Tour Guide
- Sporting Activities
- Recreation Facilities
- Parades
- Playground Duty
- Fetes

User Instructions

POWER/BATT LOW

A "constant green light" appears when power is turned ON. If there is a "blinking green light" then voltage is low. At this point, the battery voltage is 3.1V At 3.0V the device powers off automatically. Please recharge immediately.

CONNECT

When JLH-213T is turned ON, a constant red light indicates connection normal. Or see P. XX (Initial ID Setup process)

MUSIC OUT

See P. XX (Laser Pointer/ Guitar Pickup/Electronic Guitar Out/ Music Out/ Lapel Mic User Instructions)

POWER/CONNECT

Press the middle once to turn power ON. Hold down for 3 seconds to power OFF

CONNECT: After purchase, initialize connection / See P. XX (Initial ID setup process)

CHARGE DC +5V

Precautions/See P. XX (Charger Information/Specifications)

BELT CLIP

See P. XX (Transmitter Configuration)

RED-CHARGING GREEN - CHARGED

See P. XX (Charger Information/Specifications)

CONNECT: After purchase, initialize connection / See P. XX (Initial ID setup process)

Frequency range:2.4GHZ ISM Band
Frequency response:20HZ-20KHZ
S/N Ratio:105dB
Loss: Less than 0.05%
Sampling frequency:24bit/48khz
System delay:8ms
Channel:26 (region-dependent)
Lithium battery charging time: ~2.5 hours
Lithium battery endurance: ~24 hours
Maximum output: MONO 6dBv
Dimensions:24×43×124mm (excl. protrusion)
Mass :252 g (Incl. internal lithium battery)

Charging Instructions

Make sure the devices are fully charged before use

Please provide MMUSB/USB dual-connector cable

Can use any computer/mobile phone charger (Output voltage: DC 5V)

Verify that the cable connector matches the JLH-213T/R port specifications

Align the external cable connector into the JLH-213T/R port and it should insert easily (the port becoming detached due to use is not covered by warranty)

Charging time: ~2.5 hours for JLH-213T/R

Same location: Red light means charging, green light means fully charged and power automatically cut off

Double safeguard with over-discharge protection during use and over-charge protection during charging

Automatic regulation of charging current to extend battery

Charging specifications

Lithium rechargeable battery: DC3.6V/800mA
Charging current:Ð500mA
Charger cable:
Charging input current: DC 5V/500mA
Charging saturation voltage: DC-4.2V

Accessories

STANDARD ACCESSORIES

User Manual
Internal mic
Neck strap
USB charger cable

OPTIONAL ACCESSORIES

Laser pointer
Belt clip
3.5mm-6.3mm cable

This brochure is printed with recycled paper & Soy Ink

Sanha®