



Designed by **DMC Concept**

Digital Media Controller DMC T4500

Features:

- Reliable capacitive touch panel with longer life cycle
- Able to configure as Master / Slave / Stand alone
- PC out and monitor out signal can be same or different
- Able to use Monitor Out & MIC during OFF mode
- One touch selection with buzzer sound
- Electronic Volume Control
 - Increase or decrease digital volume
- Pre-programmed projector protocol
 - Easy self-programming

Technical Specifications

Input:

- PC 1 Signal - VGA (D Sub 15 pins female)
- PC 1 Audio - 3.5mm mini jack
- PC 2 Signal - VGA (D Sub 15 pins female)
- PC 2 Audio - 3.5mm mini jack
- PC 3 Signal - VGA (D Sub 15 pins female)
- PC 3 Audio - 3.5mm mini jack
- 6.35mm MIC IN
- Composite Video Signal-RCA connector
- Composite Audio Signal-RCA connector

Output:

- RS232 (Internal connector)
- Monitor Out - 150MHz - VGA (D Sub 15 pins female)
- PC Signal - 150MHz (Internal connector)
- Video Signal (Internal connector)
- PC Audio (Internal connector)
- Video Audio (Internal connector)

Selector:

- Projector On / Off (with LED indicator)
- MIC On / Off (with LED indicator)
- PC Selector PC 1 / PC 2 / PC 3 (with LED Indicator)
- Monitor Out Selector PC 1 / PC 2 / PC 3 (with LED indicator)
- Video Selector (with LED indicator)
- Blank (toggle button with LED indicator)
- Sync (toggle button)
- Source (toggle button with LED indicator)
- Volume Up (digital)
- Volume Down (digital)
- Mute (with LED indicator)

Power Supply:

- DC 12v adapter (internal connector)

